



# DRV2 and X2DRV Drivers Comparison

Specifications and features of both tension control systems



## DRV2

(6910-448-109)

24 or 48 volts DC  
(E-stop for MTB  
requires 48 volt)

4.5 amps per channel

24 volt = -2.4 volts  
48 volt = -4.8 volts

0-10 volts DC

Brk A ±  
Brk B ±

In A  
In B

2.95 W x 6.86 H x 7.28 D

DRV2 can be used with any TB, ATTB/ATTC, MTB brakes or magnetic particle size 20 or smaller.

## X2DRV

(6910-448-305)

24 volt only

4 amps per channel

Up to -5 volts in a 24 volt system

0-10 volts DC  
4-20 ma

Bk1 ±  
Bk2 ±

In Bk1  
In Bk2

2.5 W x 7.6 H x 5.35 D

X2DRV also has an auxiliary input for use as additional roll diameter compensation or for use in open loop control. X2DRV includes auxiliary 10 volt external power source.

X2DRV can be used with any TB, ATTB/ATTC or Magnetic particle size 10 or smaller.